

# Contacts 5

Standard & Photo Editions

Dialing Documentation



This Contacts 5™ dialing documentation assumes the reader already understands the basic fundamentals of using the built-in Palm OS Address Book and the Palm Operating System.

## Setting Up Bluetooth/IR Dialing

The screenshots used for this tutorial were taken on a Palm Tungsten device. As a result, the screenshots may not fully resemble the setup screen of your handheld.

Note: At this time, Contacts 5 does not support dialing via a Bluetooth memory stick module.



1) Tap the Prefs icon in the Palm OS launcher to modify the system preferences.

## Preferences

**Select a set of preferences:**

General	Communication
Personal	Other

Bluetooth Connection Network Phone

2) Tap the Communication category and then tap Phone (displayed in the list).

## Preferences

Phone

**Select the connection for your phone applications.**

**Connection:**

Infrared to GSM Phone
Serial to GSM Phone
Edit Connections...

3) Tap the Connection trigger to pop-up the list of available connections. From the list, tap Edit Connections...

Done

Test

- If you are connecting via Bluetooth...

**Preferences** Connection

**Available Connections:**

- Palm Modem US/Canada
- Palm Modem UK
- IBM WorkPad Modem
- Cradle/Cable**
- IR to a PC/Handheld
- Infrared to GSM Phone
- Serial to GSM Phone

Done New... Edit... Delete

4) If you do not already have a connection to connect to your GSM Phone via Bluetooth, tap New... to create a new connection.

**Edit Connection** ⓘ

**Name:** BT to GSM Phone

**Connect to:** ▼ Phone

**Via:** ▼ Bluetooth

**Device:** Tap to Find

**Model:** ▼ Standard GSM

OK Cancel Details...

5) Enter a name for the new connection. The following settings should be selected:

Connect to: Phone

Via: Bluetooth

Device: \*\*Tap the button to find the phone you wish to use for dialing\*\*

Model: Standard GSM \*\*If another driver is required, select it instead of Standard GSM\*\*

\*If you need to enter any other information so your Palm OS device can communicate with your phone, tap Details... and enter the required information.

6) Tap OK to save the new connection.

**Edit Connection**



**Name:** BT to GSM Phone

**Connect to:** ▼ Phone

**Confirmation**



**Would you like this to be the default connection for your phone applications?**

Yes

No

7) If you are prompted to make this connection the default phone connection, tap Yes.

**Preferences**

Connection

**Available Connections:**

Palm Modem US/Canada

Palm Modem UK

IBM WorkPad Modem

Cradle/Cable

IR to a PC/Handheld

Infrared to GSM Phone

Serial to GSM Phone

**BT to GSM Phone**

Done

New...

Edit...

Delete

8) Make sure the new connection is selected in the Available Connections list and then tap Done.

## Select the connection for your phone applications.

### Connection:

- Infrared to GSM Phone
- Serial to GSM Phone
- BT to GSM Phone**
- Edit Connections...

Done




Test

9) Make sure the new connection is selected and then tap Done.


10) Next, tap the home icon to return to the launcher.

11) From the launcher, open Contacts 5™.

## Bill Reez

 Work: 271-661-9001  
 Home: 271-626-3251  
 E-mail: bill-rz@hotmail.com

12) When a record is selected in Contacts 5™ (or displayed in this example), tap the Dial option.



## Dial Phone Number



**Bill Reez**

Work: 271-661-9001

Home: 271-626-3251

Palm OS Dialer

Phor

271 61

Handspring Treo Dialer

Kyocera/Qualcomm pdQ

Samsung Series

ToneDial® Software

☐ Add



**13)** The Dial Phone Number screen is displayed. Select a phone number from the list which you would like to dial.

\*Make sure the dialing device is set to Palm OS Dialer. You can modify the dialing device by tapping the Dial Using... button.

**14)** Tap Dial to dial the phone number.

## Dial Phone Number



**Bill Reez**

Work: 271-661-9001

Home: 271-626-3251

**Dial**



**Bill Reez**

**2716619001**

**Connecting**

Cancel

**15)** The selected phone number will now be dialed using your GSM Phone (via Bluetooth).

Visit <http://www.pdapformance.com> for more information on using Contacts 5.

-----

## **About**

This documentation has been written and produced entirely by PDA Performance, Inc. SmartContacts™, SmartContacts Version 5™, and RapidEdit™ are trademarks of PDA Performance, Inc. All names, numbers, and other information use in these examples are fictional. They are for demonstration purposes only. Pursuant with copyright laws, this manual may not be copied, in whole or in part, without the written consent of PDA Performance.

© 2005 PDA Performance, Inc. All rights reserved.