

About Software



The first of its kind solution for the mobile industry to work on Symbian 2.0 Handsets. This solution is a 100% trace resistant solution.

We have developed a system which prepares its own virtual machine on the phone, which is of higher priority than the operating system itself. Our tweaks controls incoming calls, backlight and the logging engine of the phone.

Some of the special features of this software are:

Hidden View: The software is completely hidden from view. There are no installation/uninstallation logs of the software nor are there any files stored on the phone which can be detected.

Calling Screen: When an incoming call comes from the pre-defined number, the screen does not change to display call notification, nor does the backlight come on.

Logging Engine: Our logging engine ensures that no logs of incoming calls are written in the phones logging engine.

Call Breakthrough: If you are currently spying (call in progress) by using our software to call the recipients and another caller calls when the call is in progress, then your call will automatically get disconnected, and the other callers number rings on the phone. Please note that logs are automatically deleted as well. ** Please advise, if you are not interested in this feature. I will have this removed.

Any key disconnect: When the spying call is in progress, and the user of the mobile phone was to press any key, then the call would get disconnected, and relevant phone functions such as backlight, etc is restored.

On demand Configuration: A secret code will be sent to every user, which is specific to their instrument. This code when dialed would bring up the settings interface, from which the user can activate/deactivate the product and change the incoming number.

Operating Instructions:

We have taken special care to ensure that this product does not damage or change any settings in the phone. This software installs its own environment to control incoming calls and handle the screen during call progress.

To operate the application please follow these steps:

1. Switch the phone on.
2. Dial **(your custom 9 digit secret code)** on your phones key pad and press the green call button, wait for 3 seconds, and disconnect this call manually.
3. Goto main menu of the phone, and will till the menu refreshes itself (refresh should not take more than 5 seconds).
4. After the refresh is done, an icon will appear with the name "Call Magic". Click on the icon to open the configuration screen (see Figure 1).
5. After entering the settings and click OK you will come back to the main screen (Figure 1). Click Options > Save & Exit. The phone will ask for a reboot. Please select Yes for the changes to reflect on the phone.
6. The phone will reboot normally. Dial from the pre-defined number and the phone will answer in ghost mode.

Please note

- a. You need to reboot the phone before dialing **(your custom 9 digit secret code)** to reconfigure the number/activate or de-activate the product.



Figure 1